

## USING THE PE PLUS POKER DENOMINATION SET CHIP

A set chip, or "denomination setup chip" is a chip that you temporarily install on the MPU circuit board to enable the bill validator.

It essentially gives permission to the machine to enable the bill validator.

To enable the bill validator on a PE+:

- Turn the machine off.
- Remove the MPU board
- Remove the current chip in the "Program" socket.
- Install the SET chip in the Program socket.  
(make sure to install the chip with the notch in the same direction as the chip you removed).
- Put the MPU board back in the machine and turn the power on

Follow the directions on the screen -- use the Jackpot Reset key to set the correct denomination (\$0.05, \$0.25, etc.), and use the Deal/Draw button to toggle the "Disabled/Enabled" option to "Enabled."

**IMPORTANT!** Make sure to press the white "self test" button to save the settings, and wait until you see "Options Saved" on the screen.

Once you've done that:

- Turn the machine off
- Remove the MPU board
- Remove the SET chip from the Program socket and put your game program back in its place (make sure to install the chip with the notch in the same direction as the chip you removed)
- Install the MPU board again
- Turn the machine on -- your bill validator should now work.

(COURTESY OF KNAGL ON NEW LIFE GAMES)